



Cable designation		
AWD35 OG - 1		
Cable marking	[Symbol]	
Cable colour (Orange)	[Symbol]	
Conductor size (mm²)	[Symbol]	
Colour code of electric cables		
Code	Colour	
BK	Black	
BN	Brown	
RD	Red	
OG	Orange	
YE	Yellow	
GN	Green	
BU	Blue	
VT	Violet	
GY	Grey	
WH	White	
PK	Pink	
Description		
C1	B7	Connector, 66-pole
C29	C2	Connector 21-pole, Instr-Roof
C83	B4	Connector, 1-pole, yellow, VIS
C100	B6	Connector, 66-pole
C103	B4	Connector, 66-pole
C103	F2	Connector, 66-pole
C103	B3	Connector, 66-pole
C103	B3	Connector, 66-pole
C1384	C7	Joint connector, 12-pole, BOL, near E32
C1384	E8	Joint connector, 12-pole, BOL, near E32
C1384	E8	Joint connector, 12-pole, BOL, near E32
C1384	D8	Joint connector, 21-pole, BOL, beside S1010 behind panel K
C1384	E7	Joint connector, 21-pole, BOL, beside S1010 behind panel K
C1384	D7	Joint connector, 21-pole, BOL, beside S1010 behind panel K
C1395	D4	Joint connector, 21-pole, BOL, beside S1010 behind panel K
C1395	E4	Joint connector, 21-pole, BOL, beside S1010 behind panel K
C1395	D4	Joint connector, 21-pole, BOL, beside S1010 behind panel K
C1396	C4	Joint connector, 1-pole, BOL, beside R8
C1415	E2	Joint connector, BOL, beside C29
C1441	E4	Connector, 12-pole, BOL, behind panel K
C1441	D5	Connector, 12-pole, BOL, behind panel K
C1441	E4	Connector, 12-pole, BOL, behind panel K
E32	F4	Control unit, CUV
F1020	E3	Fuse, light for BOL-system, in P2
F1021	F2	Fuse, aux power supply, in P2
P2	F8	Central electric unit
R8	F4	Relay, stop light
R1036	F3	Relay, BOL 15-relay, in central electric unit
S139	B8	Switch, lighting
S141	B5	Switch, multi function
S1010	D8	Switch, BOL, behind panel K

sheet 3

sheet 3



Circuit Diagram:

BOL

Drawing No.- 1773575-2-2
Sheet-Rev:

N.B. The copyright and ownership of this drawing including associated computer data are and will remain ours. They must not be copied, used or brought to the attention of any third party without prior permission (C) Scania, Sweden

- 1. VIS15.VT at E32-D21 moved to C1384-1
- 2. to P2-D4
- 3. VIS172.RD at C29-18 moved to C1415-2
- 4. VIS7.OG at E32-C1 moved to C1384-2
- 5. VIS69.VI at E32-D16 moved to C1384-3
- 6. VIS7.VI at E32-C10 moved to C1384-4
- 7. VIS78.GY VIS40.GY at E32-B1 moved to C1384-5
- 8. to S26-3
- 9. VIS210.GY at E32-D4 moved to C1384-6
- 10. VIS211.GN at E32-D2 moved to C1384-7
- 11. VIS88.VI at E32-C13 moved to C1384-8
- 12. VIS92.VI at E32-D10 moved to C1384-9
- 13. VIS46.GY at E32-L3 moved to C1384-10
- 14. VIS319.OG at R8-8 moved to C1396-1

STD 4247